SANTAK® BLAZER SERIES LINE-INTERACTIVE UPS







KEY FEATURE

- · Microprocessor control guarantees high reliability
- · Equipped with Boost and Buck AVR to stabilize output voltage
- · Wide input voltage & frequency range, comply with generator
- \cdot Surge protection for both power line and data line(phone / modem) \cdot Built-in DC start function enables UPS to be started up without AC power supplied
- · Super-fast charger shortens the charging time to 2-4 hours

SPECIFICATION

- · Auto charging even though the UPS is off
- · Auto restart while mains recovery
- USB HID Smart Battery interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS and Linux
- $\cdot\;$ Full protection against over-discharge, overcharge, overload
- · Sealed lead-acid, maintenance free battery

1410117	Nominal Voltage	220VAC, 50/60Hz		
INPUT	Voltage Range	162 - 268 VAC		
	Connection	IEC320-10A inlet		
	Voltage Regulation	220VAC +/-10% (Battery mode)		
	Frequency Regulation	50Hz or 60Hz +/-1Hz (Battery mode)		
	Waveform	AC mode:pure sine wave; battery mode:simulated sine wave		
	Receptacles	IEC320-10A outlet		
	Transfer time	Typical 4-8ms		
	Туре	VRLA		
OUTPUT BATTERY	Recharge time	2-4hours to 90% capacity		
PRODUCT TOPOLOGY		Line Interactive		
DATA LINE SURGE PROTECTION		RJ11(600/800VA) RJ45(1000/1500/2000VA)		
COMMUNICATIONS OPERATING ENVIRONMENT		USB port, HID power device		
		Temperature: 0-40° C		
		Relative Humidity: 0-90% (non-condensing)		
		helative Humaity. 0-30% (Hon-condensing)		
	SAFETY	CE		

Model	Power Rating	Back-up Time*	Battery configuration	Net Weight (kg)	Output Receptacles	Dimensions (W x D x H) mm
BLAZER 600 Pro	600VA/360W	18 min (1 PC load)	12V/7Ah*1	4.5		
BLAZER 800 Pro	800VA/480W	22 min (1 PC load)	12V/9Ah*1	5.0	4	100 x 279 x 143
BLAZER 1000 Pro	1000VA/600W	18 min (2 PCs load)	24V/7Ah*2	8.8	6	139 x 365 x 195
BLAZER 1500 Pro	1500VA/900W	25 min (2 PCs load)	24V/9Ah*2	10.3		
BLAZER 2000 Pro	2000VA/1200W	25 min (2 PCs load)	24V/9Ah*2	10.3		

^{*} All internal batteries are default as STK brand, any other battery brand might be applied without prior notice.

In the interests of continuous product improvement, all specifications are subject to change without notice.













^{*} It's approximate and may vary with equipment, configuration, battery age, temperature, etc.