

COMCAST GROUP

Package	SKU	Data Rate	Reach (km)	Wavelength (nm)	TX output (dBm)	RX Sensitivity (dBm)	Power Consumption	Interface	Temp
SFP+	XGXP-8596-02D	10G	0.3	850	-6 ~ -1	-10	<1.0W	LC	C/I
SFP+	XGXP-1396-02D(A)	10G	2	1310	-6 ~ -0.5	-14.4	<1.2W	LC	C/I
SFP+	XGXP-1396-10D(A)	10G	10	1310	-6 ~ -0.5	-14.4	<1.2W	LC	C/I
SFP+ RX	XGXP-1396-10D(A)-RX	10G	10	1310	-	-14.4	<1.2W	LC	C/I
SFP+	XGXP-1396-40D(A)	10G	40	1310	-1 ~ 4	-15	<1.2W	LC	C/I
SFP+	(C)XP-1596-40D(A)	10G	40	1550	-1 ~ 3	-16	<1.4W	LC	C/I
SFP+	(C)XP-1596-80D(A)	10G	80	1550	-1 ~ 4	-23	<1.5W	LC	C/I
SFP+	(C)XP-1596-A0D(A)	10G	100	1550	1 ~ 5	-25	<1.8W	LC	C/I
SFP+ CWDM	(C)XP-CXX96-40D(A)	10G	40	CWDM	-1 ~ 3	-16	<1.5W	LC	C/I
SFP+ CWDM	(C)XP-CXX96-80D(A)	10G	80	CWDM	-1 ~ 4	-23	<1.6W	LC	C/I
SFP+ DWDM	(C)XP-DH(C)XX96-40D(A)	10G	40	DWDM (50G HZ)	-1 ~ 3	-16	<1.5W	LC	C/I
SFP+ DWDM	(C)XP-DXX96-40D(A)	10G	40	DWDM (100 G HZ)	-1 ~ 3	-16	<1.5W	LC	C/I
SFP+ DWDM	(C)XP-DH(C)XX96-80D(A)	10G	80	DWDM (50G HZ)	-1 ~ 4	-23	<1.6W	LC	C/I
SFP+ DWDM	(C)XP-DXX96-80D(A)	10G	80	DWDM (100 G HZ)	-1 ~ 4	-23	<1.6W	LC	C/I
SFP+ tunable	XGXP-DWT96-80D	10G	80	1568~1529	-1 ~ 3	-23	<1.65W	LC	C/I
SFP+ BIDI	XPBL-XXYY96-10D(A)	10G	10	1270/1330	-6 ~ -1	-14.4	<1.0W	LC	C/I
SFP+ BIDI	XPBL-XXYY96-20D(A)	10G	20	1270/1330	-6 ~ -0.5	-15	<1.0W	LC	C/I
SFP+ BIDI	XPBL-XXYY96-40D(A)	10G	40	1270/1330	0 ~ 5	-15	<1.0W	LC	C/I
SFP+ BIDI	XPBL-XXYY96-60D(A)	10G	60	1270/1330	0 ~ 5	-20	<1.5W	LC	C/I
SFP+ BIDI	XPBL-XXYY96-80D(A)	10G	80	1490/1550	0 ~ 4	-23	<1.5W	LC	C/I

XFP	XGXF-8596-02D	10G	0.3	850	-6 ~ -1	-10	<2.0W	LC	C
XFP	XGXF-1396-02D	10G	0.3	1310	-6 ~ -1	-15	<2.0W	LC	C
XFP	XGXF-1396-10D	10G	2	1310	-6 ~ -1	-15	<2.0W	LC	C
XFP RX	XGXF-1396-10D-RX	10G	10	1310	-	-15	<0.8W	LC	C
XFP	XGXF-1396-40D	10G	40	1310	-1 ~ 4	-15	<2.0W	LC	C
XFP	XF-1596-40D(A)	10G	40	1550	-1 ~ 4	-16.5	<2.5W	LC	C/I
XFP	XF-1596-80D(A)	10G	80	1550	0 ~ 5	-24	<3W	LC	C/I
XFP CWDM	XF-CXX96-40D(A)	10G	40	CWDM	-1 ~ 4	-16.5	<2.5W	LC	C/I
XFP CWDM	XF-CXX96-80D(A)	10G	40	CWDM	0 ~ 4	-24	<3W	LC	C/I
XFP CWDM	XF-DC(H)XX96-40D(A)	10G	40	DWDM (50G HZ)	-1 ~ 4	-16.5	<2.5W	LC	C/I
XFP CWDM	XF-DXX96-40D(A)	10G	40	DWDM (100 G HZ)	-1 ~ 4	-16.5	<2.5W	LC	C/I
XFP CWDM	XF-DC(H)XX96-80D(A)	10G	80	DWDM (50G HZ)	0 ~ 5	-24	<3W	LC	C/I
XFP DWDM	XF-DXX96-80D(A)	10G	80	DWDM (100 G HZ)	0 ~ 5	-24	<3W	LC	C/I
XFP tunable	XGXF-DWT96-80D-2	10G	80	1568~1529	-1 ~ 4	-24	<3.5W	LC	C
XFP BIDI	XFBL-XXYY96-10D(A)	10G	10	1270nm/1330 nm	-5 ~ 0	-15	<2.0W	LC	C/I
XFP BIDI	XFBL-XXYY96-40D(A)	10G	40	1270nm/1330 nm	0 ~ 5	-15	<2.0W	LC	C/I
XFP BIDI	XFBL-XXYY96-60D(A)	10G	60	1270nm/1330 nm	0 ~ 5	-20	<2.0W	LC	C/I
XFP BIDI	XFBL-XXYY96-80D(A)	10G	80	1490nm/1550 nm	-1 ~ 4	-24	<2.5W	LC	C/I