

Multimeter DUT120C



Specification

Range

DC Voltage (V)	400mV/4V/40V/400V/600V
AC Voltage (V)	4V/40V/400V/600V
DC current (A)	400μA/4mA/40mA/400mA
AC current (A)	400μA/4mA/40mA/400mA
Resistance (Ω)	400 Ω/4KΩ/40KΩ/400KΩ//4MΩ/40MΩ
Capacitance (F)	4nF/40nF/400nF/4μF/40μF/100μF
Frequency (Hz)	10Hz-100KHz

Overview

DUT120C is 4000 count notebook, type auto-ranging digital multimeter with following advantage: complete function, stable, performance, high accuracy, low power consumption, novel structure. High. Degree of current. Frequency. Duty cycle, resistance, capacitance, diode forward voltage drops and continuity, and become an ideal choice for measurement.

Meter Description

1. LCD Display
2. DC&AC Voltage and current, Resistance, Capacitance, Diode,
3. Continuity measurement selector (SELEC BUTTON)
4. Relative Measurement (REL Button)
5. Function Selection Switch
6. Hz/% (V, μA, mA and HZ/% , Function)
7. Data Hold (Hold Button)
8. Positive input end (Red Test Lead)
9. Negative Input End Black Lead)

